

Part-turn actuator			Motor										AUMA power class switchgear	
Type	Operating time for 90° in seconds	Max. torque [Nm]	Motor type	Nominal power ¹⁾ P _N [kW]	Speed [rpm]	Oper- ating capacitor ²⁾ [μF]	Nomi- nal cur- rent ³⁾ I _N [A]	Max. current ⁴⁾ I _{max} [A]	Starting current I _A [A]	cos φ	Over- current protection device setting [A]	Contact- tor	Thyristor	
SQ 05.2	3	150	VW00063-2-0,06	0.06	3,360	70	2.6	4.0	14	0.96	4.0	A1	B1	
	4.5		VW00063-4-0,04	0.04	1,680	50	2.6	3.7	14	0.96	3.7	A1	B1	
	6		VW00063-4-0,02	0.02	1,680	35	2.7	3.2	5.4	0.98	3.2	A1	B1	
	9		SW00063-4-0,01	0.01	1,680	35	1.7	1.8	4.9	0.84	1.8	A1	B1	
	12		SW00063-8-0,01	0.01	840	25	1.7	1.7	4.9	0.82	1.7	A1	B1	
	17						1.8	1.8	2.1	0.99	1.8	A1	B1	
	25													
SQ 07.2	50	300												
	3		VW00063-2-0,12	0.12	3,360	100	4.7	7.0	14	0.91	7.0	A1	B1	
	4.5		VW00063-4-0,06	0.06	1,680	70	4.7	6.5	14	0.91	6.5	A1	B1	
	6		VW00063-4-0,03	0.03	1,680	50	3.5	4.4	8.5	0.98	4.4	A1	B1	
	9		SW00063-4-0,01	0.01	1,680	35	2.6	3.1	5.4	0.98	3.1	A1	B1	
	12		SW00063-8-0,01	0.01	840	25	2.6	3.0	5.4	0.98	3.0	A1	B1	
	17						1.6	1.9	4.9	0.82	1.9	A1	B1	
SQ 10.2	25	450												
	50													
	6		VW00063-4-0,10	0.10	1,680	80	4.3	5.6	8.8	0.98	5.6	A1	B1	
	9		SW00063-4-0,06	0.06	1,680	60	4.3	5.7	8.8	0.98	5.7	A1	B1	
	12		SW00063-4-0,04	0.04	1,680	50	2.9	3.9	7.7	0.96	3.9	A1	B1	
	17		SW00063-4-0,02	0.02	1,680	35	2.7	3.2	5.4	0.98	3.2	A1	B1	
	25		SW00063-4-0,01	0.01	1,680	25	1.7	1.8	4.9	0.84	1.8	A1	B1	
SQ 12.2	35	600												
	50													
	9		VW00063-2-0,19	0.19	3,360	110	6.0	7.2	14	0.90	7.2	A1	B1	
	12		VW00063-4-0,10	0.10	1,680	80	4.3	5.6	8.8	0.98	5.6	A1	B1	
	17		SW00063-4-0,06	0.06	1,680	60	2.9	3.9	7.7	0.96	3.9	A1	B1	
	25		SW00063-4-0,04	0.04	1,680	50	2.7	3.5	7.7	0.96	3.5	A1	B1	
	35		SW00063-4-0,02	0.02	1,680	35	2.7	3.2	5.4	0.98	3.2	A1	B1	
SQ 14.2	50	900												
	75													
	108													
	9		VW00063-2-0,19	0.19	3,360	110	6.0	7.2	14	0.90	7.2	A1	B1	
	12		VW00063-4-0,10	0.10	1,680	80	4.3	5.6	8.8	0.98	5.6	A1	B1	
	17		SW00063-4-0,06	0.06	1,680	60	2.9	3.5	7.7	0.96	3.5	A1	B1	
	25		SW00063-4-0,04	0.04	1,680	50	2.7	3.2	5.4	0.98	3.2	A1	B1	
SQ 14.2	35	1,200												
	50													
	75													
	108													
	20		VW00063-2-0,19	0.19	3,360	110	6.0	7.2	14	0.90	7.2	A1	B1	
	30		VW00063-4-0,10	0.10	1,680	80	4.3	5.6	8.8	0.98	5.6	A1	B1	
	40		SW00063-4-0,06	0.06	1,680	60	2.9	3.9	7.7	0.96	3.9	A1	B1	
SQ 14.2	60	2,400												
	85													

Notes on table

- 1) Nominal power P_N Mechanical power output at motor shaft at running torque of part-turn actuator (corresponds to approx. 35 % of maximum torque).
The consumed electrical power can be calculated using the following formula:
 $P = U \times I \times \cos \varphi$
- 2) Operating capacitor For VW/SW motors, operating capacitors are integrated within the motor.
- 3) Nominal current I_N Current at running torque
- 4) Max. current I_{max} Current at maximum torque

Notes on installation and sizing

Motor data	Motor data is approximate. Due to usual manufacturing tolerances, there may be deviations from the values given.																		
Motor protection	To protect against overheating, thermoswitches or PTC thermistors are embedded in the motor windings.																		
Actuators without integral controls (AUMA NORM): Thermoswitches or PTC thermistors have to be considered within the external controls (refer to terminal plan).																			
Note: Failure to connect thermoswitches or PTC thermistors shall void the warranty for the motor.																			
Rating of the thermoswitches																			
<table border="1"> <thead> <tr> <th colspan="2">AC current</th> <th colspan="2">DC current</th> </tr> </thead> <tbody> <tr> <td>250 V, 50 – 60 Hz</td><td></td> <td>60 V</td><td>1.0 A</td> </tr> <tr> <td>$\cos \varphi = 1$</td><td>2.5 A</td> <td>42 V</td><td>1.2 A</td> </tr> <tr> <td>$\cos \varphi = 0.6$</td><td>1.6 A</td> <td>24 V</td><td>1.5 A</td> </tr> </tbody> </table>				AC current		DC current		250 V, 50 – 60 Hz		60 V	1.0 A	$\cos \varphi = 1$	2.5 A	42 V	1.2 A	$\cos \varphi = 0.6$	1.6 A	24 V	1.5 A
AC current		DC current																	
250 V, 50 – 60 Hz		60 V	1.0 A																
$\cos \varphi = 1$	2.5 A	42 V	1.2 A																
$\cos \varphi = 0.6$	1.6 A	24 V	1.5 A																
Actuators with AM or AC integral controls:																			
Thermal motor protection is already integrated.																			
Mains voltage, mains frequency	Permissible variation of mains voltage: $\pm 10\%$ Permissible variation of mains frequency: $\pm 5\%$																		
Terminal plan	<table border="1"> <thead> <tr> <th>Part-turn actuators</th> <th>Motor (type)</th> <th>Terminal plan</th> </tr> </thead> <tbody> <tr> <td>SQ 05.2 – SQ 14.2</td> <td>VW.../SW...</td> <td>TPA01R1AA-101-000</td> </tr> </tbody> </table> For further information refer to "Technical data Part-turn actuators SQ 05.2 – SQ 14.2 for open-close duty with 1-phase AC motors"			Part-turn actuators	Motor (type)	Terminal plan	SQ 05.2 – SQ 14.2	VW.../SW...	TPA01R1AA-101-000										
Part-turn actuators	Motor (type)	Terminal plan																	
SQ 05.2 – SQ 14.2	VW.../SW...	TPA01R1AA-101-000																	
Switchgear sizing	For motor operation, reversing contactors (mechanically, electrically and electronically locked) or thyristors (electronically locked) can be used.																		
Actuators without integral controls (AUMA NORM):																			
Switchgear are supplied by the customer. We recommend specification of switchgear suitable for their rated operating power/motor power in compliance with the assigned AUMA power class.																			
Switchgear assignment to AUMA power classes:																			
<table border="1"> <thead> <tr> <th>AUMA power class</th> <th>Reversing contactor Rated operating power acc. to EN 60947-4-1 Utilization category AC-3</th> <th colspan="2">Reversing contactor Motor power according to UL/CSA at</th> </tr> </thead> <tbody> <tr> <td></td> <td>400 V AC</td> <td>480 V AC</td> <td>600 V AC</td> </tr> <tr> <td>A1</td> <td>4.0 kW</td> <td>5.0 hp</td> <td>5.0 hp</td> </tr> </tbody> </table>				AUMA power class	Reversing contactor Rated operating power acc. to EN 60947-4-1 Utilization category AC-3	Reversing contactor Motor power according to UL/CSA at			400 V AC	480 V AC	600 V AC	A1	4.0 kW	5.0 hp	5.0 hp				
AUMA power class	Reversing contactor Rated operating power acc. to EN 60947-4-1 Utilization category AC-3	Reversing contactor Motor power according to UL/CSA at																	
	400 V AC	480 V AC	600 V AC																
A1	4.0 kW	5.0 hp	5.0 hp																
<table border="1"> <thead> <tr> <th>AUMA power class</th> <th>Thyristor Rated operating current acc. to EN 60947-4-2 Utilization category AC-53a</th> </tr> </thead> <tbody> <tr> <td>B1</td> <td>400 V AC 6 A</td> </tr> </tbody> </table>				AUMA power class	Thyristor Rated operating current acc. to EN 60947-4-2 Utilization category AC-53a	B1	400 V AC 6 A												
AUMA power class	Thyristor Rated operating current acc. to EN 60947-4-2 Utilization category AC-53a																		
B1	400 V AC 6 A																		
Actuators with AM or AC integral controls:																			
Required switchgear in power classes A1 or B1 are directly integrated in AM or AC controls.																			